



FSM-2000 Fire Monitoring System



- ▶ **Easy installation and operation**
- ▶ **Importing floor plans from AutoCAD**
- ▶ **Zoom and pan**
- ▶ **Automatic allocation of detection points in floor plan**
- ▶ **Comprehensive event logging**
- ▶ **Up to four panels with 2000 detection points at maximum can be connected**
- ▶ **Can be connected with FPA-5000, FPA-1200, UEZ 2000 LSN, BZ 500 LSN**
- ▶ **Different language versions available**

The FSM-2000 Fire Monitoring System is a graphical user interface for displaying and monitoring small to medium fire alarm systems with up to 2000 detection points. It is designed for four panels of the FPA-5000, FPA-1200, UEZ 2000 LSN or BZ 500 LSN at maximum.

Functions

Installation and Operation

A wizard guides you through the installation as well as the configuration in a few steps. Logically arranged graphics and icons allow to capture events precisely and to initiate appropriate measures.

Importing Floor Plans of AutoCAD

You can import floor plans of AutoCAD as dwf-file. The software automatically allocates the detector list of the fire panel to the floor plan.

Authorizations

You can set up as many operators as required and classify them according to their tasks into one of the three authorization groups: Operator, installer or administrator. A maximum of two operators can be logged on to the system at the same time.

Zoom and Pan

These two functions offer a comfortable navigation in the floor plan. With the zoom function it is possible to increase or minimize specific areas. With the pan function the floor plan can be moved in any direction.

Event Logging

In the event log all procedures and actions are recorded. You can generate statistics, make backups, print the event log and search according to various criteria.

Connectivity

You can connect up to 2000 detection points and four panels to the FSM-2000. It is working with the fire panels FPA-5000, FPA-1200, UEZ 2000 LSN and BZ 500 LSN.

Language Versions

The FSM-2000 Fire Monitoring System is in different language versions available:

- German/English
- Spanish/English
- Italian/English
- Dutch/English
- Polish/English

Installation/Configuration Notes

Hardware Preconditions:

- USB port
- CD-ROM

- 3.5" disk drive
- 4 COM ports
- RAM 1024 MB (server), 512 MB (client)
- Hard drive memory of 10 GB
- Network card 100 Mbit

Software Preconditions:

- Windows 2000, Windows XP, Windows 2003 Server (German and English operating system)
- Internet Explorer version 5.0 or 6.0
- MSDE 2000
- Microsoft IIS 5.0 (Windows 2000, Windows XP), Microsoft IIS 6.0 (Windows 2003 Server)

Parts Included

Quant.	Component
1	CD for Installation
1	USB-Dongle
1	Floppy-disk with the file Dongle.crp

Ordering Information

FSM-2000 Fire Monitoring System DE/EN FSM-2000

Additionally order:
 - Interface Converter OVS
 - Connection Cable DSUB 9F-9M
 - IOS 0020 A 20 mA Communication Module (FPA-5000/FPA-1200) or SM 20 Interface Module (UEZ 2000 LSN / BZ 500 LSN)

FSM-2000-ES Fire Monitoring System ES/EN FSM-2000-ES

Additionally order:
 - Interface Converter OVS
 - Connection Cable DSUB 9F-9M
 - IOS 0020 A 20 mA Communication Module (FPA-5000/FPA-1200) or SM 20 Interface Module (UEZ 2000 LSN / BZ 500 LSN)

FSM-2000-IT Fire Monitoring System IT/EN FSM-2000-IT

Additionally order:
 - Interface Converter OVS
 - Connection Cable DSUB 9F-9M
 - IOS 0020 A 20 mA Communication Module (FPA-5000/FPA-1200) or SM 20 Interface Module (UEZ 2000 LSN / BZ 500 LSN)

FSM-2000-NL Fire Monitoring System NL/EN FSM-2000-NL

Additionally order:
 - Interface Converter OVS
 - Connection Cable DSUB 9F-9M
 - IOS 0020 A 20 mA Communication Module (FPA-5000/FPA-1200) or SM 20 Interface Module (UEZ 2000 LSN / BZ 500 LSN)

Ordering Information

FSM-2000-PL Fire Monitoring System PL/EN FSM-2000-PL

Additionally order:
 - Interface Converter OVS
 - Connection Cable DSUB 9F-9M
 - IOS 0020 A 20 mA Communication Module (FPA-5000/FPA-1200) or SM 20 Interface Module (UEZ 2000 LSN / BZ 500 LSN)

Accessories

IOS 0020 A 20 mA Communication Module IOS 0020 A
 provides one interface each of S20, RS232 and S1

Interface Converter OVS 3002108620

Connection Cable DSUB 9F-9M DB EK 822 9F-9M

Americas:
 Bosch Security Systems, Inc.
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
 security.sales@us.bosch.com
 www.boschsecurity.us

Europe, Middle East, Africa:
 Bosch Security Systems B.V.
 P.O. Box 80002
 5600 JB Eindhoven, The Netherlands
 Phone: + 31 40 2577 284
 Fax: +31 40 2577 330
 emea.securitysystems@bosch.com
 www.boschsecurity.com

Asia-Pacific:
 Robert Bosch (SEA) Pte Ltd, Security Systems
 11 Bishan Street 21
 Singapore 573943
 Phone: +65 6258 5511
 Fax: +65 6571 2698
 apr.securitysystems@bosch.com
 www.boschsecurity.com