



# DS7460i Dual-zone Input Module



- ▶ Supervises two protection loops
- ▶ Can be used in UL Listed fire and security applications
- ▶ DIP switch programmable

The DS7460i Dual-zone Input Module works with compatible multiplex systems, uses two multiplex zone addresses, and monitors up to two separate zones. It is DIP switch programmable and provides two supervised input zones to connect conventional normally-open (NO) or normally-closed (NC) contacts.

UL UOXX: Control Units for Fire-protective Signaling Systems (UL864)

UL UTOU: Household Fire Warning System Units (UL985)

CE

## Functions

### Supervises Two Protection Loops

The two protection zones are designed to monitor NO or NC dry contacts. They are supervised using 47 kΩ end-of-line (EOL) resistors.

Zone 1 may be used as a magnetic contact by mounting a magnet in conjunction with the reed switch and removing the EOL resistor for Zone 1. Zone 1 may not be used as a magnetic contact and used to monitor other contacts at the same time.

## Certifications and Approvals

Listings and Approvals:	UL AMCX: Central-station Burglar Alarm Units (UL1610)
	UL AOTX: Local Burglar Alarm Units and Systems (UL609)
	UL APAW: Police Station Connected Burglar Alarm Units and Systems (UL365)
	UL NBSX: Household Burglar Alarm System Units (UL1023)

## Installation/Configuration Notes

### Compatibility Information

Control Panels	D9412GV2, D7412GV2, and D7212GV2 Control Panel
	D9412G, D7412G, and D7212G Control Panel
	D9124 Fire Alarm Control Panel
	DS7400Xi Control Panel
Multiplex Modules	D8125MUX Multiplex Bus Interface
	DS7430 Multiplex Expansion Module
	DS7436 Multiplex Expansion Module

*The DS7460i Module requires a multiplex expansion module to connect to the control panels.*

### Fire Applications

For UL Listed fire installations, normally-open (NO) contacts must be used. For fire installations, order Multiplex Fire Zone EOL Resistors (P/N: 28010) in the quantity needed.

## Wiring

Maximum Impedance: 4.05  $\Omega$  at +20°C (+68°F) nominal

Distance (approximate)	Size
76 m	0.65 mm
193 m	1.02 mm
250 ft	22 AWG
600 ft	18 AWG

Refer to the multiplex expansion module's reference guide for multiplex wiring requirements. The recommended wiring to the control panel is quad (four-wire) cable. Do not use shielded or twisted pair cable.

**Note** If used in fire applications, 18 AWG wire is required.

## Parts Included

Quantity	Component
1	Dual-zone input module
2	Multiplex-zone EOL resistor (P/N: 26069)
1	Hardware pack
1	Literature pack

## Technical Specifications

### Circuit Parameters

Initiating Device Circuit Type:	Class B (Style A)
Signaling Line Circuit Type:	Class B (Style 4)
Zone Requirements:	Two multiplex addresses

### Environmental Considerations

Temperature (Operating): 0°C to +50°C (32°F to +122°F)

### Power Requirements

Current Draw: 1 mA maximum

## Ordering Information

DS7460i Dual-zone Input Module	DS7460i
Provides two supervised input zones to connect conventional normally-open (NO) or normally-closed (NC) contacts. It is DIP switch programmable.	

**Americas:**  
 Bosch Security Systems  
 130 Perinton Parkway  
 Fairport, New York, 14450, USA  
 Phone: +1 585 223 4060  
 Fax: +1 800 289 0096  
 security.sales@us.bosch.com  
 www.boschsecurity.us

**Europe, Middle East, Africa:**  
 Bosch Security Systems B.V.  
 P.O. Box 80002  
 5600 JB Eindhoven, The Netherlands  
 Phone: +31 40 27 83955  
 Fax: +31 40 27 86668  
 emea.securitysystems@bosch.com  
 www.boschsecurity.com

**Asia-Pacific:**  
 Bosch Security Systems Pte Ltd  
 38C Jalan Pemimpin  
 Singapore 577180  
 Phone: +65 6319 3450  
 Fax: +65 6319 3499  
 apr.securitysystems@bosch.com  
 www.boschsecurity.com

**Represented by**