


BOSCH

Invented for life

ND 200 LSN Panic Button



- ▶ **Panic button in LSN technology**
- ▶ **For connecting to an LSN intrusion control panel**
- ▶ **Alarm and tampering transmission via LSN bus**
- ▶ **Tamper contact**
- ▶ **Cable can be surface- or flush-mounted**
- ▶ **Cap with cover as trigger protection (optional)**

The ND 200 LSN panic button is used for unobtrusively and manually triggering alarms at work places that are in potential danger of being held up, such as banks, jewelry shops, businesses, private households etc.

Certifications and Approvals

Region	Certification	
Germany	VdS	G 101037, C ND 200 LSN
Europe	CE	ND 200 LSN

Parts Included

Type	Qty.	Component
ND 200 LSN	1	Panic button incl. adhesive seal

Technical Specifications

Operating voltage (LSN part)	+12 V to 30 V
Current consumption (line voltage)	Approx. 0.5 mA
Ambient temperature	-0 °C to +50 °C
Ambient climates	DIN 40040 R14
Protection category	IP 40
Housing	
• Material	ABS
• Color	RAL 9002 (housing) Gray (cover)
Weight	Approx. 70 g
Dimensions (D x H)	81 x 31 mm
Environmental class	2

Ordering Information

ND 200 LSN Panic Button **4998117564**

For unobtrusively and manually triggering alarms at work places that are in potential danger of being held up

Accessories

Cap with cover **3902115343**

For additional protective cover to prevent false alarms

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by